



## Разъединитель предохранителей 2П, 25А

Тип **FCFDC10DI-2-SOL**  
 № для зак. **137257**

Abbildung ähnlich

### Программа поставок

Ассортимент			Разъединители с предохранителем
Область применения			Жилые здания Коммерческие здания Открытое пространство
Описание			Защита ветви генератора фотогальваники Сигнализация срабатывания сигнализирует о срабатывании плавкой вставки: 50 - 400 В мигающая, 400 - 1000 В постоянная для цилиндрических плавких вставок для применения в фотогальванике пломбируемый
Подключение			без функции мигания
Номинальное напряжение	$U_e$	V	1000
Расчетный рабочий ток 240 В	$I_e$	A	25
Величина			10 x 38
Полюсы			2-полюсн.

### Технические характеристики согласно ETIM 6.0

Low-voltage industrial components (EG000017) / Fuse switch disconnecter (EC001040)			
Electric engineering, automation, process control engineering / Low-voltage switch technology / Off-load switch, circuit breaker, control switch / Fuse switch disconnecter (ec1@ss8.1-27-37-14-01 [AKF058010])			
Version as main switch			No
Version as safety switch			Yes
Max. rated operation voltage $U_e$ AC		V	0
Rated permanent current $I_u$		A	25
Rated operation power at AC-23, 400 V		kW	0
Conditioned rated short-circuit current $I_q$		kA	10
Rated short-time withstand current $I_{cw}$		kA	0
Suitable for fuses			Shape C1-C3
Number of poles			2
With error protection			No
Type of electrical connection of main circuit			Screw connection
Suitable for ground mounting			No
Suitable for front mounting 4-hole			No
Suitable for busbar mounting			No
Type of control element			-
Position control element			Front side
Motor drive optional			No
Motor drive integrated			No
Version as emergency stop installation			No
Degree of protection (IP), front side			IP20